



## Microtest Pentascanner Specs

Provided by [www.AAATesters.com](http://www.AAATesters.com)

# PentaScanner® Products

[ *high-performance cable certification tools* ]

### **PentaScanner 350**

#### **with 2-Way**

#### **Injector+... Testing**

#### **Category 5 Links**

#### **for Superior**

#### **Performance.**

### **PentaScanner+ with**

#### **Super Injector+...**

#### **The smallest, most**

#### **accurate Category 5**

#### **tester available.**

If you are evaluating a new Category 5 tester, look no further than the company that invented handheld cable testing. PentaScanner products set the standard for LAN cable testing, certification and accuracy.

### **PentaScanner 350 with 2-Way Injector+**

Superior link quality is required for high speed applications. Now you can test Category 5 links for superior performance. PentaScanner 350's Performance Grading puts the focus on link quality, ensuring that your cabling, connectors and installation will meet requirements now and well into the future. Performance Grading measures and rates the quality of high performance links by analyzing the headroom available for high-speed applications. PentaScanner 350 can actually differentiate links that are marginally passing from links that have up to 70 times better signal-to-noise ratios.

PentaScanner 350 measures Quality Bands from 1 to 7, with 1 being

a marginally passing Category 5 link and 7 being the highest link performance. Now you can tell those links that marginally pass and may require costly rewiring from the links that are highly reliable.

PentaScanner 350 includes all the proven features in PentaScanner+, such as a 21-second Autotest, full cable certification, extensive cabling library, automatic increment of circuit ID, replaceable, rechargeable battery, Flash ROM for field updates and storage of 500 Autotests. And, if you already own PentaScanner+, it's easy to upgrade to PentaScanner 350.

Don't just test to Category 5 requirements – test for superior performance!

### **PentaScanner+ with Super Injector+**

When only single-ended testing is required, PentaScanner+ with Super Injector+ is the most economical tester available. PentaScanner+ far exceeds EIA/TIA TSB-67 Level II

accuracy requirements. Its superior accuracy is the result of years of accumulated knowledge and experience testing and certifying network cabling systems. In fact, PentaScanner+ provides accuracy indistinguishable from a network analyzer.

### **Features of PentaScanner 350 and PentaScanner+**

- Test all pair combinations to 100 MHz.
- Measure Near-End Crosstalk (NEXT), attenuation, Return Loss, resistance, impedance, length, capacitance, Attenuation-to-Crosstalk Ratio (ACR), Power Sum NEXT and wiremap.
- Monitor and graph network traffic
- Print complete, easy-to-read certification reports.
- Allow you to program test limits and customize Autotests.
- Store up to 500 Autotests.
- Allow flash ROM updates from the field.
- Include a replaceable, rechargeable battery for all day use.
- Incorporate a graphical backlit display screen and on-line help.
- Designed for durability.
- Compatible with Microtest's PC-based MT Crimp™ for complete physical infrastructure management.
- Free, unlimited technical support.

### **Tools and Leadership You Can Trust**

When you need the job done right the first time, there's only one choice – Microtest, the worldwide leader in cable certification and diagnostic technology.



# PentaScanner® Products

[ *high-performance cable certification tools* ]

## Product Package

- PentaScanner 350 with 2-Way Injector+ or PentaScanner+ with Super Injector+
- Replaceable, rechargeable battery
- User documentation
- (2) Test patch cables
- (2) Modular 8 adapters
- Serial cable
- (1) AC adapter with the PentaScanner+ or (2) AC adapters with the PentaScanner 350
- Soft carrying case

## PentaScanner Specifications

### Part Numbers

- PentaScanner 350 with 2-Way Injector+ #8180-xx\*
- PentaScanner+ with Super Injector+ #8150-xx\*

\*Call Microtest Sales for U.S. and International part numbers

### Physical Characteristics

- Dimensions: 10.2 cm x 20.3 cm x 5.5 cm (4' x 8' x 2.15')
- Weight: 0.79 kg (1 lb., 12 oz.)

### Power

- Rechargeable, replaceable battery pack
- Built in charger using AC adapter
- External battery charger available as an accessory
- Battery life: 8 hours daily operation
- AC: 9V DC – 1 amp AC adapter for continuous operation or charging

### Environmental

- Operating Temperature: 0° to 50°C (32° to 122°F)
- Storage Temperature: -10° to 55°C (14° to 131°F)
- Operating Humidity (non-condensing): 10 to 90%
- Storage Humidity: 5 to 95%

### Measurement Ports

- BNC and 36-pin connector that withstands in excess of 20,000 mating cycles
- Testing of all four pairs on Modular 8 (RJ-45) is fully supported

## Serial Port

- Connector and Cable: DB-9F
- Baud rate: 300 to 38,400 baud
- Protocol: Parity - NONE  
8 Data bits, 1 Stop bit
- Handshake: XON/XOFF, RTS/CTS

## Memory

- Test Storage: Up to 500 complete Autotest results can be stored
- Control: Flash memory allows electronic upgrading in remote locations

## Autotest Functions

- Full suite of tests to determine if cable meets generic cabling or network type requirements (TIA TSB-67, ISO Class C, D, 10-Base T, Token Ring, Fast Ethernet, ATM 155 etc.)
- Up to 20 user definable Autotest programs

## Near-End Crosstalk (NEXT)

- Tests all six pair combinations from both ends\*
- Power Sum NEXT computed from both ends for all 4 pairs\*
- Frequency range 0.7 to 100 MHz
- Sweep Mode 0.1, 0.2, 0.5 MHz steps (linear) or TIA (user selectable)
- Dynamic Range: Measurement dynamic range > 75 dB
- Measurement Accuracy: Calculated per TIA TSB-67 error model (see NEXT and Attenuation Specifications table)
- Measurement resolution: 0.1 dB

\*Requires 2-Way Injector+ for simultaneous measurements from both ends

## Attenuation

- Tests all four pairs using far end active signal injection
- Frequency range 1.0 to 100 MHz
- Sweep mode: Swept 1- 100 MHz using 1 MHz steps or fixed points (1, 2, 4, 5, 8, 10, 16, 20, 25, 31.25, 62.5, and 100 MHz)
- Dynamic Range: 0 - 50 dB
- Measurement Accuracy: Calculated per TIA TSB-67 error model (see NEXT and Attenuation Specifications table)
- Measurement resolution: 0.1 dB

## NEXT and Attenuation Measurement Performance Specifications

NEXT and Attenuation Performance Parameters @ 100 MHz	Testing Thru 36 Pin Connector		Testing Thru Mod 8 Adapter
	Typical	Max	Typical
Dynamic Accuracy (dB)	0.3	0.5	0.3
Residual NEXT (dB)	67	62	45
Output Signal Balance (dB)	50	43	40
Common Mode Rejection (dB)	35	38	34
Random Noise (dB)	78	75	78
Transmit Return Loss (dB)	26	23	20
Receive Return Loss (dB)	22	17	17
NEXT Accuracy (dB) @ 100 MHz	0.5 (*1)	0.9 (*1)	1.5 (*2,3)
Atten. Accuracy (dB) @ 100 MHz	0.3 (*4)	0.6 (*4)	0.6 (*3,4)

### \*Notes:

- (1) NEXT accuracy is calculated at the Basic Link Limit (29.3 dB) per error model in TSB-67 A.3
- (2) NEXT accuracy is calculated at the channel Limit (27.1 dB) per error model in TSB-67 A.3
- (3) Performance assumes a high performance modular 8 plug
- (4) Attenuation accuracy calculated per error model in TSB-67 A.3

### Return Loss

- Test all four pairs from both ends\*
- Frequency Range: 1.0 to 100.0 MHz
- Measurement Range: 0 to 20.0 dB
- Measurement resolution: 0.1 dB

\*Requires 2-Way Injector+ for simultaneous measurements from both ends

### Noise

- Impulse Noise: Detects the occurrence of narrow impulse type events exceeding an adjustable threshold of ± 0.262, 0.524, 1.0, 2.0 or 2.5 volts. Instantly displays up to 200 impulse noise events per second. Graphically logs and displays impulse events for up to 25 hours. Termination impedance: 200 ohms.
- Peak to Peak Noise: Measures the peak to peak voltage of steady state noise signals. Range: 0 to 3,000 mVpp into 100 ohms. Bandwidth: 3dB from 40 kHz to 30 MHz

### Wire Map

- Uses Injector for complete mapping of wiring at both ends of the cable
- Finds miswires, opens, shorts, split pairs
- Includes test of shield if connected

### Length

- Range: 0 to maximum distance where maximum distance = 915 meters (3000 ft) for twisted pair cable = 1200 meters (4000 ft) for coaxial cable
- Accuracy: ± K ± Length Resolution ± NVP uncertainty where K=4% of length or 0.6 meters (2 ft), whichever is greater Length Resolution: 0.3 meters (1 ft)

### Impedance

- Range: 40 to 200 ohms
- Accuracy: 5 ohms
- Resolution: 2 ohms

### Loop Resistance

- Range: 0 to 10000 ohms
- Accuracy: ± 0.3 ohms @ 0 to 15 ohms ± 2% @ 15 to 109 ohms ± 5% @ >109 to 5000 ohms ± 10% @ 5000 to 10000 ohms
- Resolution: 0.1 ohms @ 0 to 200 ohms 1.0 ohms @ 200 to 1000 ohms

### Capacitance

- Range: 0 to 100,000 pF
- Accuracy: ± 20 pf @ 0 to 200 pF ± 10% @ 200 to 100,000 pF

### High Voltage Input/Protection:

- The test interface withstands input hazard conditions that arise from normal telephone interfaces (48 VDC at less than 80 mA) or 24 VAC power used to power many telephone keysets TSB-67 Level II Accuracy is maintained through Quality Band 7

www.microtest.com



Microtest, Inc.  
4747 North 22nd Street  
Phoenix, Arizona 85016-4708  
TEL (602)952-6400  
(800)526-9675  
FAX (602)952-6401  
E-mail:sales@microtest.com

Microtest Enterprise Group  
22 Cotton Road  
Nashua, NH 03063  
TEL (603)880-0300  
(800)880-5644  
FAX (603)880-7229  
E-mail:sales@microtest.com

Microtest GmbH  
Am Soeldnermoos 17  
D-85399  
Munich-Hallbergmoos, Germany  
TEL +49 (89) 607 6861 0  
FAX +49 (89) 607 6861 1

Microtest Europe  
2a Kingfisher House,  
Northwood Park, Gatwick Road  
Crawley, West Sussex, RH102XN  
United Kingdom  
TEL +44 (1293) 894 000  
FAX +44 (1293) 894 008  
E-mail:salesmte@microtest.com

©1995, 1998 Microtest, Inc. PentaScanner is a registered trademark and MTCrimp is a trademark of Microtest, Inc. All rights reserved. Specification and price change privileges reserved. Some of the product names mentioned herein have been used for identification purposes only and may be trademarks and/or registered trademarks of their respective companies. Information subject to change without notice. For the latest information, visit the Microtest Web Site at www.microtest.com Document # 2938-6506-01 Rev. 01